How to send Motion Detected Snapshot to Email account via SMTP server? (Applicable to FCS-1010, 1030, 1040, WCS-2010, 2030)

Configure FCS-1010, 1030, 1040, WCS-2010, 2030 SMTP, motion detection and Application.

Configuring FCS-1010, 1030, 1040, WCS-2010, 2030

 Input the SMTP server information. In this case, SMTP server address is "mail.ddcasia.com.tw", account name is "test", enter password for SMTP authentication. Please enter Recipient Email address and Sender Email address. Sender email must be entered.

Home	SMIP		
System	1st SMTP (mail) server	mail.didcasia.com.tw	
Security	1st SMTP account name	test	
• Network	1st SMTP password	•••••	
DONS & UPhP	1st rocipient email address	tmmy@ddcasa.com.tw	
Mai & FTP	2nd SMTP (mail) server	NUMBER OF THE OWNER	
Video	and SMTP account name		
🔹 Audo	2nd SMTP ressword		
 Motion detection 	and partment anal address		
 Camera control 	Cander arrist attents	Record Reddonaria comp bui	
 Application 	Server Britar actives inf	humancessition.cv	
 View log file 	Built-in FTP server port	21	
 View parameters 	1st FTP server		
 Factory default 	1st FTD server cost	21	
Aversion : 0101h	Lot FTP yorker port		
	13. PTP user name		
	1st PTP password		
	1st FTP remote folder	<u></u>	
	I: 1st FTP passive mode		
	2nd FTP server	10 M	
	2nd FTP server port	21	1

- 2. Configuring motion detection by enable motion detection first. Name the new windows and click new, adjust sensitivity and percentage.
- 3. Wave your hand in front of the camera, once you see the green bar turns red, it means the motion has triggered.



- 4. Application, please configure as below if you want to send snapshot to the email address input via the SMTP account. Note the weekly schedule, the configuration below means 24 hours 7 days a week the motion detection is active.
- 5. Remember to tick the Detect motion in test (Which is the motion detection windows you just named).

Home	Weekly schedule			-
• System	FSun FMon FTue FWed FThu FFn FSat			
Security	snapshots begin at 00.00.00 [hhmmmiss]			
• Network	snapshots stop at 23:59:59 [hhmmuss]			
• DONS & UPhP	☐ All the time except for the above schedule			
Mai & FTP	ABSEAD AG A ANY			
🛨 Video	Snapshot file name prefix	video		
😧 Audo	Event operation			
Motion detection	General			
 Camera control 	84945975	Delay 3 second(s) before detect	ing the next event	
 Application 		Send 1 pre-event mage(s) when	n evenit occurs	
 View log file 	Trigger condition	2 2 510		
 View parameters 		Finput is high Finput is low		
Factory default		P Input is rising P Input is faling		_
		Detect motion in :		
Version : 0101b		IP test	52	
	95 63	Note: Motion detection must be setup	frst	
	Trigger action			
		Trigger output alarm while input of	ondition matched	
		Trigger output alarm while motion	detected	
		P Upload snapshots while input cond	ation matched	-

6. Please tick Send snapshot by email, once the above triggering condition has met, the snapshot will be automatically send to the email address via

SMTP server.



7. Snapshot received.

🗮 Event snapshots: Digital input is low - Message (Plain Text)	JØX				
Bie Edit View Insert Format Tools Actions Help					
From: timmy@ddcasia.com.tw Te: timmy@ddcasia.com.tw Cc: Subject: Event snapshots: Digital input is low	Sent: 2006/2/6 (星期一) 下午 03-26				
Attachments: @video_1_pre.jpg (10 KB); @video_2_brg.jpg (10 KB); @video_3_pos.jpg (10 KB)					
*** Event snapshots: Digital input is low *** From: http://192.168.123.195 video_1_pre.jpg: 2006/02/06.15:25:41 video_2_trg.jpg: 2006/02/06.15:25:42 video_3_pos.jpg: 2006/02/06.15:25:43 Note: FCS-1040 P/T/Z IP Camera	X				
	I				