



LevelOne

GNC-0105T

32-bit 10/100/1000Mbps Ethernet PCI Card

User Manual

V5.0-0708

FCC STATEMENT

The adapter has been tested and found to comply with the limits for a class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation.

This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- 1) This device may not cause harmful interference.
- 2) This device must accept any interference received, including interference that may cause undesired operation.

CE DECLARATION OF CONFORMITY

In compliance with the EMC Directive 89/336/EEC, the adapter meets the requirements of the following standards:

- EN55022
- EN55024

SAFETY NOTICES



Caution:

Do not use this product near water, for example, in a wet basement or near a swimming pool.

Avoid using this product during an electrical storm. There may be a remote risk of electric shock from lightning.



INTRODUCTION

Thank you for choosing LevelOne 10/100/1000Mbps Gigabit Ethernet Card for 32-bit PCI Bus-equipped personal computers. The 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card is ideal for speeding up data transfers for network servers and other computers, such as those used for video-conferencing, that send and/or receive large amounts of data. The 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card also includes the newest networking technologies, such as multicasting support, that use network bandwidth more efficiently and further help the card maximize data throughput.

Features

- ◆ Complies with the IEEE802.3 10Base-T, IEEE802.3u 100Base-TX and IEEE802.3ab 1000Base-T standard
- ◆ Compliant to PCI Revision 2.1/2.2
- ◆ Plug-and-Play installation
- ◆ One RJ-45 connector, Supports Auto-detects Network speed
- ◆ Supports IEEE802.1Q VLAN tagging
- ◆ Supports 10/100/1000Mbps Auto-Negotiation function
- ◆ Full Duplex support for 10/100/1000Mbps data rates
- ◆ Auto MDI-II/MDI-X crossover for all three speeds
- ◆ Built-in FIFO buffers reduces overhead of memory transfers
- ◆ 802.3x Full duplex flow control, including automatic transmission of Pause frames based on Rx FIFO thresholds
- ◆ Two LED indicators for easy diagnostic

Gigabit Ethernet Technology

Gigabit Ethernet is an extension of IEEE 802.3 Ethernet utilizing the same packet structure, format, and support for CSMA/CD protocol, full duplex, and management objects, but with a tenfold increase in theoretical throughput over 100Mbps Fast Ethernet and a one hundred-fold increase over 10Mbps Ethernet. Since it is compatible with all 10Mbps and 100Mbps Ethernet environments, Gigabit Ethernet provides a straightforward upgrade without wasting a company's existing investment in hardware, software, and trained personnel.

The increased speed and extra bandwidth offered by Gigabit Ethernet is essential to coping with the network bottlenecks that frequently develop as computers and their busses get faster and more users use applications that generate more traffic. Upgrading key components, such as your backbone and servers to Gigabit Ethernet can greatly improve network response times as well as significantly speed up the traffic between your subnets.

Gigabit Ethernet enables Twisted-Pair cable connections to support video conferencing, complex imaging, and similar data-intensive applications. Likewise, since data transfers occur 10 times faster than Fast Ethernet, servers outfitted with Gigabit Ethernet NIC's are able to perform 10 times the number of operations in the same amount of time.

Fast Ethernet Technology

The growing importance of LANs and the increasing complexity of desktop computing applications are fueling the need for high performance networks. A number of high-speed LAN technologies have been proposed to provide greater bandwidth and improve client/server response times. Among them, 100BASE-T (Fast Ethernet) provides a non-disruptive, smooth evolution from the current 10BASE-T technology. The non-disruptive and smooth evolution nature, and the dominating potential market base, virtually guarantees cost effective and high performance Fast Ethernet solutions in the years to come.

100Mbps Fast Ethernet is a new standard specified by the IEEE 802.3 LAN committee. It is an extension of the 10Mbps Ethernet standard with the ability to transmit and receive data at 100Mbps, while maintaining the CSMA/CD Ethernet protocol. Since the 100Mbps Fast Ethernet is compatible with all other 10Mbps Ethernet environments, it provides a straightforward upgrade and takes advantage of the existing investment in hardware, software, and personnel training.

UNPACKING AND INSTALLATION

This chapter provides unpacking and installation information for the LevelOne 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card.

Unpacking

CAUTION: *Under ordinary circumstances, the 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card will not be affected by static charge as may be received through your body during handling of the unit. However, there are special circumstances where you may carry an extraordinarily high static charge, and possibly damage the card and/or your computer. It is good practice to eliminate all static electricity by touching a ground (an unpainted metal area of your computer chassis, for example) before performing any installations.*

Open the shipping carton and carefully remove all items, ascertain that you have:

- GNC-0105T
- CD Manual/Driver

If any item is found missing or damaged, please contact your local reseller for replacement.

Installing the Gigabit Ethernet Card

1. Shut down the computer, unplug its power cord, and remove the chassis cover.
2. Insert the contact edge of the Gigabit Ethernet card into the connector of any available PCI Bus Master Expansion slot. Press the card firmly into the connector such that the card's contacts are fully seated in the connector, this card can be put either in 32-bit or 64-bit PCI slot, but it is recommended that the card be put in the 64-bit PCI slot to have the maximum performance.
3. Install the bracket screw and secure the card to the computer chassis.

4. Cover the computer's chassis.
5. Switch computer power on. If the BIOS section of your computer's boot program is Plug-and-Play compliant, then at power-up the BIOS will automatically configure any newly installed the Gigabit Ethernet Card.

NOTE: *Due to a fault in some Plug-n-Play BIOS programs, it happens occasionally that a newly installed adapter is assigned an Interrupt Number which is already assigned to another device. In such a case, the conflict of Interrupt Number will cause faults in the behavior of both devices. Then it is necessary to run the CMOS Setup utility, and manually assign a non-conflicting Interrupt Number.*

Connecting the Network Cable

Four pair of Cat.5 UTP or STP cable with RJ-45 connector is required for the 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card. You can use standard or crossover cable to connect the switch MDI-X or MDI-II port, because the 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card will adjust the correct signal automatically.

Software Installation

Before you connect the 32-bit PCI 10/100/1000Mbps Gigabit Ethernet Card to the network, you have to install the network driver first. The driver for each networking operating system is under a separate directory.

LED INDICATORS

Two LED indicators: **Link, Activity**.

Link Indicator

This indicator lights green when the Gigabit Card is connects to 10/100/1000Mbps Gigabit Ethernet Network.

Activity Indicator (ACT)

This indicator blinking green will be transmitting or received data on the network.

TECHNICAL SPECIFICATIONS

General	
Standards	IEEE 802.3 10Base-T Ethernet IEEE 802.3u 100Base-TX Fast Ethernet IEEE 802.3ab 1000Base-T Gigabit Ethernet IEEE 802.3x Flow Control
Protocol	CSMA/CD
Data Transfer Rate	Ethernet: 10Mbps (half), 20Mbps (full) Fast Ethernet: 100Mbps (half), 200Mbps (full) Gigabit Ethernet: 1000Mbps (half), 2000Mbps (full)
Topology	Star
Network Cables	Ethernet: 2-pair UTP Cat. 3,4,5 , EIA/TIA- 568 STP Fast Ethernet: 2-pair UTP Cat. 5, EIA/TIA-568 STP Gigabit Ethernet: 4-pair UTP Cat.5, EIA/TIA-568 STP
LED Indicator	Link, Activity
RJ-45 Port	Auto MDI-II/MDI-X port
Physical and Environmental	
Power Consumption	4 W (Max)
Temperature	Operating: 0° ~ 40° C, Storage: 0° ~ 70° C
Humidity	Operating: 10% ~ 90%, Storage: 5% ~ 90%
Dimensions	59 x 120 x 15mm (W x D x H)
EMI:	FCC Class, CE Mark Class